

Siemens  
EcoTech



SIMATIC S7-1500, analog input module AI 16xU BA, 16-bit resolution accuracy 0.5%, 16 channels in groups of 16, common mode voltage 4 V DC, diagnostics, hardware interrupts; delivery including infeed element, shield bracket and shield terminal: front connector (screw terminals or push-in) to be ordered separately

General information	
Product type designation	AI 16xU BA
HW functional status	from FS01
Firmware version	V1.0.0
<ul style="list-style-type: none"> <li>FW update possible</li> </ul>	Yes
Product function	
<ul style="list-style-type: none"> <li>I&amp;M data</li> </ul>	Yes; I&M0 to I&M3
<ul style="list-style-type: none"> <li>Isochronous mode</li> </ul>	No
<ul style="list-style-type: none"> <li>Prioritized startup</li> </ul>	No
<ul style="list-style-type: none"> <li>Measuring range scalable</li> </ul>	No
<ul style="list-style-type: none"> <li>Scalable measured values</li> </ul>	No
<ul style="list-style-type: none"> <li>Adjustment of measuring range</li> </ul>	No
Engineering with	
<ul style="list-style-type: none"> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V16 with HSP 312 / V17
<ul style="list-style-type: none"> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.5 SP3 / -
<ul style="list-style-type: none"> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	V1.0 / V5.1
<ul style="list-style-type: none"> <li>PROFINET from GSD version/GSD revision</li> </ul>	V2.3 / -
Operating mode	
<ul style="list-style-type: none"> <li>Oversampling</li> </ul>	No
<ul style="list-style-type: none"> <li>MSI</li> </ul>	Yes
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Power	
Power consumption from the backplane bus	0.85 W
Power loss	
Power loss, typ.	0.75 W
Analog inputs	
Number of analog inputs	16
<ul style="list-style-type: none"> <li>For voltage measurement</li> </ul>	16
permissible input voltage for voltage input (destruction limit), max.	12 V; 12 V continuous, 30 V for max. 1 s
Input ranges (rated values), voltages	
<ul style="list-style-type: none"> <li>0 to +5 V</li> </ul>	No
<ul style="list-style-type: none"> <li>0 to +10 V</li> </ul>	No
<ul style="list-style-type: none"> <li>1 V to 5 V</li> </ul>	Yes
— Input resistance (1 V to 5 V)	10 MΩ

<ul style="list-style-type: none"> <li>• -1 V to +1 V <ul style="list-style-type: none"> <li>— Input resistance (-1 V to +1 V)</li> </ul> </li> <li>• -10 V to +10 V <ul style="list-style-type: none"> <li>— Input resistance (-10 V to +10 V)</li> </ul> </li> <li>• -2.5 V to +2.5 V</li> <li>• -25 mV to +25 mV</li> <li>• -250 mV to +250 mV</li> <li>• -5 V to +5 V <ul style="list-style-type: none"> <li>— Input resistance (-5 V to +5 V)</li> </ul> </li> <li>• -50 mV to +50 mV</li> <li>• -500 mV to +500 mV</li> <li>• -80 mV to +80 mV</li> </ul>	<p>Yes</p> <p>10 MΩ</p> <p>Yes</p> <p>10 MΩ</p> <p>No</p> <p>No</p> <p>No</p> <p>Yes</p> <p>10 MΩ</p> <p>No</p> <p>No</p> <p>No</p>
<b>Cable length</b>	
<ul style="list-style-type: none"> <li>• shielded, max.</li> </ul>	200 m
<b>Analog value generation for the inputs</b>	
Measurement principle	integrating
<b>Integration and conversion time/resolution per channel</b>	
<ul style="list-style-type: none"> <li>• Resolution with overrange (bit including sign), max.</li> <li>• Integration time, parameterizable</li> <li>• Integration time (ms)</li> <li>• Basic conversion time, including integration time (ms) <ul style="list-style-type: none"> <li>— additional conversion time for wire-break monitoring</li> </ul> </li> <li>• Interference voltage suppression for interference frequency <math>f_1</math> in Hz</li> </ul>	<p>16 bit</p> <p>Yes</p> <p>2,5 / 16,67 / 20 / 100 ms</p> <p>10 / 24 / 27 / 107 ms</p> <p>4 ms (to be considered for 1 to 5 V measurement)</p> <p>400 / 60 / 50 / 10 Hz</p>
<b>Smoothing of measured values</b>	
<ul style="list-style-type: none"> <li>• parameterizable</li> <li>• Step: None</li> <li>• Step: low</li> <li>• Step: Medium</li> <li>• Step: High</li> </ul>	<p>Yes</p> <p>Yes</p> <p>Yes</p> <p>Yes</p> <p>Yes</p>
<b>Encoder</b>	
<b>Connection of signal encoders</b>	
<ul style="list-style-type: none"> <li>• for voltage measurement</li> </ul>	Yes
<b>Errors/accuracies</b>	
Linearity error (relative to input range), (+/-)	0.1 %
Temperature error (relative to input range), (+/-)	0.006 %/K
Crosstalk between the inputs, max.	-50 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.1 %
<b>Operational error limit in overall temperature range</b>	
<ul style="list-style-type: none"> <li>• Voltage, relative to input range, (+/-)</li> </ul>	0.5 %
<b>Basic error limit (operational limit at 25 °C)</b>	
<ul style="list-style-type: none"> <li>• Voltage, relative to input range, (+/-)</li> </ul>	0.3 %
<b>Interference voltage suppression for <math>f = n \times (f_1 \pm 1 \%)</math>, <math>f_1</math> = interference frequency</b>	
<ul style="list-style-type: none"> <li>• Series mode interference (peak value of interference &lt; rated value of input range), min.</li> <li>• Common mode voltage, max.</li> <li>• Common mode interference, min.</li> </ul>	<p>40 dB</p> <p>4 V</p> <p>60 dB</p>
<b>Interrupts/diagnostics/status information</b>	
Diagnostics function	Yes
<b>Alarms</b>	
<ul style="list-style-type: none"> <li>• Diagnostic alarm</li> <li>• Limit value alarm</li> </ul>	<p>Yes</p> <p>Yes; two upper and two lower limit values in each case</p>
<b>Diagnoses</b>	
<ul style="list-style-type: none"> <li>• Monitoring the supply voltage</li> <li>• Wire-break</li> <li>• Short-circuit</li> <li>• Group error</li> <li>• Overflow/underflow</li> </ul>	<p>No</p> <p>Yes; Only for 1 ... 5 V</p> <p>No</p> <p>No</p> <p>Yes</p>
<b>Diagnostics indication LED</b>	
<ul style="list-style-type: none"> <li>• RUN LED</li> </ul>	Yes; green LED

• ERROR LED	Yes; red LED	
• MAINT LED	No	
• Monitoring of the supply voltage (PWR-LED)	No	
• Channel status display	Yes; green LED	
• for channel diagnostics	Yes; red LED	
• for module diagnostics	Yes; red LED	
<b>Potential separation</b>		
Potential separation channels		
• between the channels	No	
• between the channels, in groups of	16	
• between the channels and backplane bus	Yes	
<b>Permissible potential difference</b>		
between the inputs (UCM)	8 V DC	
Between the inputs and MANA (UCM)	4 V DC	
<b>Isolation</b>		
Isolation tested with	707 V DC (type test)	
<b>Standards, approvals, certificates</b>		
Siemens Eco Profile (SEP)	Siemens EcoTech	
Ecological footprint		
• environmental product declaration	Yes	
Global warming potential		
— global warming potential, (total) [CO2 eq]	38.6 kg	
— global warming potential, (during production) [CO2 eq]	14.4 kg	
— global warming potential, (during operation) [CO2 eq]	24.6 kg	
— global warming potential, (after end of life cycle) [CO2 eq]	-0.44 kg	
<b>product functions / security / header</b>		
signed firmware update	No	
data integrity	No	
<b>Ambient conditions</b>		
Ambient temperature during operation		
• horizontal installation, min.	-30 °C	
• horizontal installation, max.	60 °C	
• vertical installation, min.	-30 °C	
• vertical installation, max.	40 °C	
Altitude during operation relating to sea level		
• Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual	
<b>Dimensions</b>		
Width	35 mm	
Height	147 mm	
Depth	129 mm	
<b>Weights</b>		
Weight, approx.	250 g	
<b>Classifications</b>		
	<b>Version</b>	<b>Classification</b>
eClass	14	27-24-22-01
eClass	12	27-24-22-01
eClass	9.1	27-24-22-01
eClass	9	27-24-22-01
eClass	8	27-24-22-01
eClass	7.1	27-24-22-01
eClass	6	27-24-22-01
ETIM	10	EC001420
ETIM	9	EC001420
ETIM	8	EC001420
ETIM	7	EC001420

IDEA	4	3562
UNSPSC	15	32-15-17-05

Approvals / Certificates

General Product Approval



[Miscellaneous](#)

[Manufacturer Declaration](#)



[KC](#)

General Product Approval For use in hazardous locations



[FM](#)

[CCC-Ex](#)

[Miscellaneous](#)



For use in hazardous locations Maritime application

[Type Examination Certificate](#)



Maritime application Environment

[NK / Nippon Kaiji Kyokai](#)



[CCS \(China Classification Society\)](#)



Siemens EcoTech



last modified:

10/23/2025